

TX3014, Dual Priority Voice Operated Muting Module Installation Instructions

Thank you for choosing an Australian Monitor Installation Series TX3014 dual priority voice operated muting module. The TX3014 allows for muting of all other channels when signal is present on channel 1 and will also mute channel 3 and onwards when signal is present on channel 2. Installation into either the Australian Monitor Installation Series SA60, SA120, TX6000 or TX8000 is made simple by utilising a standard 'end' type connector which simply plugs into a receptacle inside the mixer or amplifier. Please follow these easy instructions for installation.

The installation of the TX3014 involves access to the inside of the mixer or amplifier. Installation should only be attempted by a qualified technician. Always turn off AC power and remove the AC power cord before attempting to access the inside of any Australian Monitor Installation Series mixer or amplifier.

For installation into the SA series mixer amplifiers: Locate the 8 pin 'end' connector found on location X3 on the mixer PCB in between the input gain pots for Ch 2 and Ch 3. This 'end' connector is divided into two separate parts consisting of 5 pins and 3 pins. Remove both of these filler plugs and discard. Connect the module to this receptacle, ensuring that the black trace found on the wires of the module is facing the front of the amplifier.

For installation into the TX6000 mixer: Locate the 8 pin 'end' connector found on location X3 on the mixer PCB in between the input gain pots for Ch 2 and Ch 3. This 'end' connector is divided into two separate parts consisting of 5 pins and 3 pins. Remove both of these filler plugs and discard. Connect the module to this receptacle, ensuring that the black trace found on the wires of the module is facing the front of the amplifier.

For installation into the TX8000 mixer: Locate the 8 pin 'end' connector found on the mixer PCB behind the input gain pot for Ch 1. This 'end' connector is divided into two separate parts consisting of 5 pins and 3 pins. Remove both of these filler plugs and discard. Connect the module to this receptacle, ensuring that the black trace found on the wires of the module is facing the front of the amplifier (so that the wires exit towards the left hand side of the mixer when looking from the front).



Engineered by Audio Telex Communications Pty Ltd, Sydney, Australia
A.B.N. 78 001 345 482 Inc in NSW

www.audiotelx.com.au

Export Sales & Corporate Head Office

Private Bag 149, Silverwater NSW 1811
149 Beaconsfield Street, Silverwater NSW 2128
Australia
Ph: 61-2- 9647 1411
Fax: 61-2-9748 2537
E-mail: ho@audiotelx.com.au

Sydney (NSW & ACT Sales)

Private Bag 149, Silverwater NSW 1811
149 Beaconsfield Street, Silverwater NSW 2128
Ph: (02) 9647 1411
Fax: (02) 9648 3698
E-mail: nsw@audiotelx.com.au

Melbourne (Vic & Tas Sales)

P.O. Box 131, Blackburn South VIC 3130
22/277 Middleborough Road, Box Hill VIC 3128
Ph: (03) 9890 7477
Fax: (03) 9890 7977
E-mail: vic@audiotelx.com.au

Brisbane (Qld Sales)

P.O. Box 871, Fortitude Valley QLD 4006
42 Commerical Road, Fortitude Valley QLD 4006
Ph: (07) 3852 1312
Fax: (07) 3252 1237
E-mail: qld@audiotelx.com.au

Adelaide (SA & NT Sales)

P.O. Box 157, Hindmarsh SA 5001
31 Walsh Street, Thebarton SA 5031
Ph: (08) 8352 4444
Fax: (08) 8352 4488
E-mail: sa@audiotelx.com.au

Perth (WA Sales)

P.O. Box 404, North Perth WA 6906
299 Fitzgerald Street, West Perth WA 6005
Ph: (08) 9228 4222
Fax: (08) 9228 4233
E-mail: wa@audiotelx.com.au

Auckland (NZ Sales)

P.O. Box 512, Albany 1331
Unit B, 11 Piermark Drive, Albany 1331
Ph: (09) 415 9426
Fax: (09) 415 9894
E-mail: audiotlx@nznet.gen.nz