



**8383
8 CHANNEL
MIXER
AMPLIFIER**

8383 is a superb full featured power mixer suitable for stage, entertainment applications. It is equipped with two 150 watt RMS and one 100 watt RMS power amplifiers.

8383 is supplied in a solid wooden cabinet, felt covered, with carry handles and protective corners for easy and safe transportation.

Features:

- Inbuilt reverberation
- Three power amplifiers
- XLR mic sockets
- Balanced and high level inputs
- Can be removed from wooden cabinet for rack mounting

Controls:

Master: Level — EXT effects — Internal reverb return — Fold back level — Headphone level — Pre or post EQ switch.

Channel: Gain — Foldback — Bass — Treble — Effects — Fader — Reverb effects switch — Fader.

Technical Specifications:

POWER OUTPUTS	150 watts × 2 left and right 100 watts × 1 into four ohms
MIC/LINE INPUTS	Six balanced XLR mic sockets phone line sockets
AUX INPUTS	Two phone sockets left and right stereo
INPUT SENSITIVITY	Mic 1.5 MV for max output Aux 100 MV for max output. Line 100 MV for max output
SIGNAL TO NOISE	Mic -70 dB. Aux -75 dB for rated output
DISTORTION	0.06% THD
FREQUENCY RESPONSE	50 Hz - 20 KHz ±3 dB
REVERB DELAY TIME	1.75 to 3.0 seconds
POWER SOURCE	240 or 120 VAC
DIMENSIONS	23 H × 53 W × 34 D (cm) in cabinet
WEIGHT	17 Kg