



DI 20 DI 50 DI 100

**AUSTRALIA'S FINEST RANGE
OF PUBLIC ADDRESS
SYSTEM AMPLIFIERS**

FEATURES:

- ★ Low impedance, balanced microphone inputs.
- ★ 8 ohm, 70 and 100 volt outputs.
- ★ XLR microphone inputs.
- ★ Tape output.
- ★ Optional 600 ohm out, DI 50, DI 100.
- ★ Optional microphone precedence, DI 50, DI 100.
- ★ Table mounting or Rack mounting, DI50, DI 100.

TECHNICAL SPECIFICATIONS:

	DI 20	DI 50	DI 100
Frequency response (-3dB)	50Hz-16.5KHz	50Hz- 16.5KHz	55Hz- 16KHz
Power output	20 watts	50 watts	100 watts
Number of microphone inputs	1	2	4
Number of auxiliary inputs	1	2	2
Microphone Sensitivity	480uv	450uv	450uv
Auxiliary input sensitivity	100mv	85mv	100mv
Signal to Noise	74dB	68dB	68dB
Outputs	4, 8, 16 ohms 100, 70, 50 v	100v, 70v, 8 ohms	100v, 70v, 8 ohms
Tape out	200mv	200mv	200mv
Tone control action	10KHz ± 17dB	± 14dB 10KHz ± 14dB	100Hz
Dimensions	28.9W × 19.7D × 6.9H cms	48.2W × 31.3D × 13.5H cms	
Weight (including packaging)	3.8 Kg	9 Kg	12.5 Kg
Fuses	1 x 1 amp 1 x 5 amp	1 x 1.5 amp 1 x 2.5 amp	1 x 2.5 amp 1 x 5 amp

ACCESSORIES:

- LD 685 600 ohm Line Drive Module DI 50, DI 100
M 585 Auxillary Input Muting Kit DI 50, DI 100